

BOSCH DCN-NG Channel Selector Panel with Backlight

Listen[®]

www.ListenTech.com

Specify Part Number

DCN-FCS

The DCN-FCS is a compact and stylish single-user audio channel selector for listening by headphone to up to 32 high quality audio channels used for distribution of interpretation and floor channels.



Features

- No audio output until the headphone is connected.
- Automatically adapts to available channels
- Stylish and modern design
- Built-in "Silent" function; no audio output until one of the keys has been pressed to eliminate audible noise from the headphones when not in use.



shown installed with DCN-FEC End Caps

Specifications

Controls and indicators		Two push-buttons (up/down) for channel selection
		Two push-buttons (up/down) for headphone volume control
		Backlit 2-digit LCD for channel number indication
Interconnection		0.14 in. (3.5 mm) stereo jack headphone connector
		Connector for external headphone
		6.6 ft. (2 m) cable with a moulded 6-pole circular connector 6-pole circular connector for loop-through interconnection
Electrical characteristics	Supply voltage	17- 40 V d.c. via DCN network cable
	Power consumption	0.8 W
Performance	Headphone	Load impedance > 32 ohm < 1 kΩ
Physical characteristics	Mounting	Flush mounted
	Dimensions	(H x W x D) 1.6 x 3.9 x 3.9 in. (40 x 100 x 100 mm)
	Weight	Weight 0.66 lbs. (0.3 kg)
	Color	Silver

Accessories



DCN-FEC DCN-NG Flush Mount End Caps

Matching end caps to give a finishing touch to the flush mounted channel selector. 2 end caps are needed per flush mount channel selector.



DCN-FCOUP DCN-NG Flush Mount Couplers

The couple pieces are to flush mount and connect the channel selector and the ends caps. 2 couple pieces are needed per flush mount channel selector.

Listen Technologies Corporation

8535 South 700 West, Suite A
Sandy, UT 84070-2515 U.S.A.
Phone: 1.801.233.8992 or 1.800.330.0891
Fax: 1.801.233.8995
Email: info@ListenTech.com

Don't miss a single sound.

